

# FICHA DEL PRODUCTO

ITEM:

Amperimetro tenaza digital, 1000 A, 600 VAC-DC, UT-206

CÓDIGO:

27150081UT

IMAGEN:



DESCRIPCIÓN  
APLICACIÓN:

AC Corriente (A) 400A/1000A  $\pm(1.5\%+5)$ , 400A/1000A  $\geq 800A$ :  $\pm(3\%+5)$   
AC Voltage (V) 4V/40V/400V/600V  $\pm(1.2\%+5)$   
DC Voltage (V) 400mV/4V/40V/400V/600V  $\pm(0.8\%+1)$   
Resistance ( $\Omega$ ) 400 $\Omega$ /4k $\Omega$ /40k $\Omega$ /400k $\Omega$ /4M $\Omega$ /40M $\Omega$   $\pm(1\%+2)$   
Frequency (Hz) 10Hz~10MHz  $\pm(0.1\%+3)$   
Temperature ( $^{\circ}\text{C}$ ) -40  $^{\circ}\text{C}$  ~ 0 $^{\circ}\text{C}$   $\pm(3\%+4)$   
0  $^{\circ}\text{C}$ ~400  $^{\circ}\text{C}$  1%+3  
400  $^{\circ}\text{C}$ ~1000  $^{\circ}\text{C}$  2%+10  
Auto range  $\checkmark$   
Diode test  $\checkmark$   
Apagado Automático  $\checkmark$   
Continuity buzzer  $\checkmark$   
Indicación de batería baja  $\checkmark$   
Pantalla retro iluminada  $\checkmark$   
Linterna  $\checkmark$